

# Application Note for SDP600 & SDP1000 Series

## Handling instructions

### Summary

SDP600 & SDP1000 series are differential pressure sensors of high quality. For taking benefit of their outstanding performance some precautions must be taken

during storage, assembly and packaging. Therefore, please read the following instructions carefully.

## 1. Processing the sensor

### Storage

Storage environment should be free from dust.

Prior to assembly or use of the sensors it is strongly recommended to store the sensors in original ESD tray packaging. For sensors that have been removed from the original packaging we recommend to store them in ESD bags.

Storage temperature in non-condensing environment shall be in the range of -40°C to 80°C (-40°F to 176°F). For long-term storage 0°C to 50°C (32°F to 122°F) temperature range is recommended.

### Assembly

***Assure that the ports of the sensor are well protected during assembly and soldering so that no dust, solder flux or other liquids can enter the flow channel.***

Please obey the soldering instruction of the datasheet.

No ***mechanical force*** should be applied to any part of the sensor during assembly or usage. Especially, no force shall be applied to the sensor pins.

### ESD (Electrostatic Discharge)

The sensor shall only be handled in ESD protected areas (EPA) under protected and controlled conditions (ground all personnel with wrist-straps, ground all non-insulating and conductive objects, exclude insulating materials from the EPA, operate only in grounded conductive floor, etc.). Protect sensor outside the EPA using ESD protective packaging.

## 2. Application in extreme environment

Avoid any kind of liquid, fatty and oil emulsive vapors inside the flow channel. It can not be guaranteed that in these cases the sensors have no drift.

Protect the sensor from dust, which could enter into the flow channel.

Make sure that in humid environment there is no condensation, which could occur inside the sensor.

The sensor is specified for operation in air and nitrogen. Please avoid aggressive or etching substances such as H<sub>2</sub>O<sub>2</sub>, NH<sub>3</sub>, etc.

Application of Sensirion differential pressure sensors to harsh environment must be carefully tested and qualified. The user is responsible for ***qualification of the sensor for use in harsh environment.***

## Revision history

Date	Version	Author	Changes
18.02.09	V1.0		Initial revision
June 2009	V1.1		Layout adapted and list of sales offices updated
April 2010	V1.2	DAT	Minor changes
February 2012	V1.3	VVO	Storage temperature range is updated

## Headquarter and Sales Offices

SENSIRION AG  
Laubisruetistr. 50  
CH-8712 Staefa ZH  
Switzerland

Phone: + 41 (0)44 306 40 00  
Fax: + 41 (0)44 306 40 30  
[info@sensirion.com](mailto:info@sensirion.com)  
[www.sensirion.com](http://www.sensirion.com)

SENSIRION Korea Co. Ltd.  
#1414, Anyang Construction Tower B/D,  
1112-1, Bisan-dong, Anyang-city,  
Gyeonggi-Province, South Korea

Phone: +82-31-440-9925~27  
Fax: +82-31-440-9927  
[info@sensirion.co.kr](mailto:info@sensirion.co.kr)  
[www.sensirion.co.kr](http://www.sensirion.co.kr)

SENSIRION Inc  
Westlake Pl. Ctr. I, suite 204  
2801 Townsgate Road  
Westlake Village, CA 91361  
USA

Phone: +1 805-409 4900  
Fax: +1 805-435 0467  
[michael.karst@sensirion.com](mailto:michael.karst@sensirion.com)  
[www.sensirion.com](http://www.sensirion.com)

SENSIRION China Co. Ltd.  
Room 2411, Main Tower  
Jin Zhong Huan Business Building,  
Postal Code 518048  
Futian District, Shenzhen, PR China

Phone: +86 755 8252 1501  
Fax: +86 755 8252 1580  
[info@sensirion.com.cn/](mailto:info@sensirion.com.cn/)  
[www.sensirion.com.cn](http://www.sensirion.com.cn)

SENSIRION Japan  
Sensirion Japan Co. Ltd.  
Shinagawa Station Bldg. 7F  
4-23-5 Takanawa  
Minato-ku, Tokyo, Japan

phone: +81 3-3444-4940  
fax: +81 3-3444-4939  
[info@sensirion.co.jp](mailto:info@sensirion.co.jp)  
[www.sensirion.co.jp](http://www.sensirion.co.jp)

Find your local representative at: <http://www.sensirion.com/rep>